

Home Center 2

FIBARO SYSTEM 2



Thank You for purchasing Home Center 2

To start using Fibaro System Home Center 2, please connect the device to power and LAN sockets, as shown below.

1. Unscrew left side panel



2. Take side panel off



3. Connect wires as shown on figure below



WARNING! Do not turn Home Center 2 on without RECOVERY pendrive.

4. Connect antenna

After connecting antenna, push POWER button to turn device on.



5. Start Your internet browser

After ca 2 minutes HC2 is ready to operate. By default HC2 awaits for Your DHCP server to assign IP address. If unsure how it works, You can set HC2 to static IP by pushing and holding RECOVERY button with power ON.

HC2 will reset to static IP **192.168.81.1**. To access HC2 login panel, please type IP address in Your web browser address bar.

6. Login to Home Center 2

After completing previous step You will access HC2 control panel. Choose Your language version and enter user name and password. Defaults are: admin / admin.



LED Indicators



POWER



LAN



INTERNET



Z-WAVE



LEARN MODE [blinking slowly] - adding device
LEARN MODE [blinking] - removing device
LEARN MODE [blinking fast] - device added / removed successfully



RECOVERY



UPDATE [blinking] - software update available



SERVICE [blinking] - software update in progress.

Back panel buttons



POWER button
Click to turn power ON

Click (at power ON) to reset device

Hold for ca 10 seconds to turn power OFF



RECOVERY button
To access RECOVERY MODE disconnect plug from power socket and hold Recovery button while plugging it back.

Click to enter LEARN MODE (add device)

Double Click to enter LEARN MODE (remove device)

Hold to set static IP.