

## RID 200 B-SERIES

### DIESEL GENERATOR SET 200 KVA



#### POWER RATING

OUTPUT RATINGS		PRIME	STANDBY
Power	kVA   kW	200   160	220   176
Current	A	288	316
Voltage	V	230 / 400	230 / 400
Frequency	Hz		50
Rated at power factor	cos φ		0,8

#### POWER RATING DESCRIPTION

##### Prime Rating

The ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

##### Standby Rating

The ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings. The alternator on this model is peak continuous rated (as defined in ISO 8528-3).

#### PRODUCT OVERVIEW

RATINGS DATA	
Order number Generator	713708
Alternator Model	Linz PRO28S B/4
Engine Type	DOOSAN - P086TI
Generator type	synchronous
Protection class	IP 23
Control Panel	RID 1000 A

#### DIMENSIONS AND WEIGHTS

LENGTH (L)	WIDTH (W)	HEIGHT (H)	WEIGHT	TANK CAPACITY
2600 mm	1200 mm	1940 mm	2030 kg	700 l

#### NOISE LEVEL

1 METER	4 METER	7 METER	10 METER
93 dB(A)	90,5 dB(A)	88 dB(A)	85 dB(A)

## RID 200 B-SERIES

### DIESEL GENERATOR SET 200 KVA



#### ENGINE TECHNICAL DATA

ENGINE TECHNICAL DATA		PRIME	STANDBY
Engine output	kW	177	199
Engine type		DOOSAN - P086TI	
Engine size		6-Cylinder; in-line	
Injection system		Direct injection in-line type	
Rotational-speed range	rpm	1500	
Bore   Stroke	mm	111   139	
Cooling system		water + air	
Speed regulation		electrical	
Compression ratio		16,4:1	
Displacement	l	8,07	
Engine w/o cooling system	kg	790	
Weight with cooling system	kg	-	

#### FUEL SYSTEM

POWER STANDARD		25%	50%	75%	100%
Fuel consumption PRIME	l	11,3	21,1	31,7	43,1
Fuel consumption STANDBY	l	12,7	23,7	35,5	48,4

#### EXHAUST SYSTEM

Silencer type		Industrial
max. exhaust gas temperature	°C	580
Exhaust gas flow	m <sup>3</sup> /h	1980

#### AIR SYSTEM

Air Filter Type		replaceable Element
Combustion air volume	m <sup>3</sup> /h	942
max. intake depression	mbar	-

#### COOLING SYSTEM

Cooling system		water + air
Cooling system capacity (Engine)	l	44
Fan power consumption	kW	5
Cooling air flow	m <sup>3</sup> /h	11400

#### LUBRICATION SYSTEM

Oil type		RID 10W40
Oil filter type		replaceable element
Total oil volume	l	15,5
Max. oil temperature	°C	120

## RID 200 B-SERIES

### DIESEL GENERATOR SET 200 KVA



#### ALTERNATOR DATA

<b>Alternator Model</b>	Linz PRO28S B/4	
<b>Generator type</b>	synchronous	
<b>Insulation Class</b>	H	
<b>Regulation Type</b>	AVR	
<b>Control System</b>	self excited	
<b>Execution</b>	brushless	
<b>Protection class</b>	IP 23	
<b>Stator Winding</b>	Double layer with auxiliary winding	
<b>Rotor Winding</b>	I	with damping cage
<b>Winding Pitch</b>	2/3	
<b>THD at full load</b>	<3%	
<b>Overspeed</b>	rpm	2250
<b>Air Flow Requirement</b>	m <sup>3</sup> /h	1920
<b>References</b>	EN60034-1	ISO8528-3 EN55011

#### ALTERNATOR PERFORMANCE DATA

VOLTAGE SERIES STAR, V	RATED POWER (125°C/40°C), KVA   KW	X <sub>d</sub>	X' <sub>d</sub>	X'' <sub>d</sub>
380   220	200   160	431 %	23,3 %	12,3 %
400   230	200   160	389 %	21,0 %	11,1 %
415   240	200   160	361 %	19,5 %	10,3 %
440   254	180   144	289 %	15,6 %	8,3 %

#### CERTIFICATIONS AND NORMS

EN60034-1	ISO8528-3	EN55011	Outdoor Noise Equipment Directive 2000/14/EC
-----------	-----------	---------	--

## RID 200 B-SERIES

### DIESEL GENERATOR SET 200 KVA



#### CONTROL PANEL

~ RID 1000 A ~

#### CONTROLLER FUNCTIONS

FUNCTIONS	RANGES, VALUES	
<b>operating modes</b>	automatic, manual, test and remote	available
<b>mains control with limits</b>	voltage, frequency, phase sequence	available
<b>generator control with limits</b>	voltage, frequency, power, phase sequence.	available
<b>engine control with limits</b>	start, stop, shutdown by alarms	available
<b>power control</b>	current, kW, kVA, kVA <sub>r</sub> , power factor	available
<b>statistic data mains</b>	voltage, frequency and current	available
<b>statistic data generator</b>	voltage, frequency and current	available
<b>fuel level control</b>	in % and in liters	available
<b>fuel consumption control and history</b>	in l/h	available
<b>working hours per day</b>	in h	available
<b>service hours</b>	in h	available
<b>battery service</b>	in h	available
<b>events log with time and date</b>	255 events	available
<b>alarm list programming</b>	77 alarms	available
<b>protocols</b>	GSM, Ethernet, Modbus, Canbus, RID protocol	available

#### REMOTE MONITORING FUNCTIONS

<b>mains voltage L1, L2, L3</b>	in V, AC	available	<b>engine temperature</b>	in °C,	optional
<b>generator voltage L1, L2, L3</b>	in V, AC	available	<b>enviroment temperature</b>	in °C,	optional
<b>genset battery voltage DC</b>	in V, DC	available	<b>generator run hours</b>	in h,	available
<b>mains power total</b>	in kW,	available	<b>generator maintanace hours</b>	in h,	available
<b>generator power total</b>	in kW,	available	<b>fuel level</b>	in L,	available
<b>mains frequency</b>	in Hz	available	<b>load on mains</b>	indication	available
<b>generator frequency</b>	in Hz	available	<b>load on generator</b>	indication	available
<b>current L1, L2, L3</b>	in A,	available	<b>mains supply</b>	indication	available
<b>power L1, L2, L3</b>	in kW,	available	<b>generator supply</b>	indication	available

#### SPECIFIC ALARMS

GENSET DOOR OPEN	FUEL TANK OPEN	AIR FILTER CLOGGING	FIRE ALARM
optional	optional	optional	optional