

## RID 200 S-SERIES

### DIESEL GENERATOR SET 200 KVA



#### POWER RATING

OUTPUT RATINGS		PRIME	STANDBY
Power	kVA   kW	200   160	220   176
Current	A	289	316,8
Voltage	V	230 / 400	230 / 400
Frequency	Hz		50
Rated at power factor	cos φ		0,8

#### POWER RATING DESCRIPTION

##### Prime Rating

The ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

##### Standby Rating

The ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings. The alternator on this model is peak continuous rated (as defined in ISO 8528-3).

#### PRODUCT OVERVIEW

RATINGS DATA	
Order number Generator	713363
Alternator Model	Linz PRO28S B/4   Leroy - Somer TAL 044 M
Engine Type	DEUTZ BF6M1013FC
Generator type	synchronous
Control Panel	RID 1000 A

#### DIMENSIONS AND WEIGHTS

LENGTH (L)	WIDTH (W)	HEIGHT (H)	WEIGHT	TANK CAPACITY
2540 mm	1050 mm	1845 mm	2070 kg	500 l

#### NOISE LEVEL

1 METER	4 METER	7 METER	10 METER
85 dB(A)	84 dB(A)	83 dB(A)	82 dB(A)

## RID 200 S-SERIES

### DIESEL GENERATOR SET 200 KVA



#### ENGINE TECHNICAL DATA

ENGINE TECHNICAL DATA		PRIME	STANDBY
Engine output	kW	183	201
Engine type		DEUTZ BF6M1013FC	
Engine size		6-Cylinder; in-line	
Injection system		Single injection pumps	
Rotational-speed range	rpm	1500	
Bore   Stroke	mm	108   130	
Cooling system		water + air	
Speed regulation		electrical	
Compression ratio		17,5	
Displacement	l	4,8	
Engine w/o cooling system	kg	708	
Weight with cooling system	kg	770	

#### FUEL SYSTEM

POWER STANDARD		25%	50%	75%	100%
Fuel consumption PRIME	l/h	12,2	23,0	34,2	46,5

#### EXHAUST SYSTEM

Silencer type		Industrial
Max. exhaust back pressure	mbar	30
max. exhaust gas temperature	°C	560
Exhaust gas flow	m <sup>3</sup> /h	2112

#### LUBRICATION SYSTEM

Oil type		RID 5W30
Oil filter type		replaceable element
Total oil volume	l	20
Max. oil temperature	°C	130

#### COOLING SYSTEM

Cooling system		water + air
Cooling system capacity	l	27,3
Max. coolant outlet temperature	°C	105
Heat dissipation (radiator)	kW	96,1
Heat dissipation (CAC)	kW	42
Fan power consumption	kW	7,2
Cooling air flow	m <sup>3</sup> /h	11520

#### AIR SYSTEM

Air Filter Type		replaceable Element
Combustion air volume	m <sup>3</sup> /h	745,6
max. intake depression	mbar	25

## RID 200 S-SERIES

### DIESEL GENERATOR SET 200 KVA



#### ALTERNATOR DATA

<b>Alternator Model</b>	Linz PRO28S B/4	Leroy - Somer TAL 044 M	
<b>Generator type</b>	synchronous		
<b>Insulation Class</b>	H		
<b>Regulation Type</b>	AVR		
<b>Control System</b>	self excited		
<b>Execution</b>	brushless		
<b>Protection class</b>	IP 23		
<b>Stator Winding</b>	Double layer with auxiliary winding		
<b>Rotor Winding</b>	with damping cage		
<b>Winding Pitch</b>	2/3		
<b>THD at full load</b>	<3%	<5%	
<b>Overspeed</b>	rpm	2250	
<b>Air Flow Requirement</b>	m <sup>3</sup> /h	1920	1044
<b>References</b>	EN60034-1	ISO8528-3	EN55011

#### CERTIFICATIONS AND NORMS

EN60034-1	ISO8528-3	EN55011	Outdoor Noise Equipment Directive 2000/14/EC
-----------	-----------	---------	--

## RID 200 S-SERIES

### DIESEL GENERATOR SET 200 KVA



#### CONTROL PANEL

~ RID 1000 A ~

#### CONTROLLER FUNCTIONS

FUNCTIONS	RANGES, VALUES	
<b>operating modes</b>	automatic, manual, test and remote	available
<b>mains control with limits</b>	voltage, frequency, phase sequence	available
<b>generator control with limits</b>	voltage, frequency, power, phase sequence.	available
<b>engine control with limits</b>	start, stop, shutdown by alarms	available
<b>power control</b>	current, kW, kVA, kVA <sub>r</sub> , power factor	available
<b>statistic data mains</b>	voltage, frequency and current	available
<b>statistic data generator</b>	voltage, frequency and current	available
<b>fuel level control</b>	in % and in liters	available
<b>fuel consumption control and history</b>	in l/h	available
<b>working hours per day</b>	in h	available
<b>service hours</b>	in h	available
<b>battery service</b>	in h	available
<b>events log with time and date</b>	255 events	available
<b>alarm list programming</b>	77 alarms	available
<b>protocols</b>	GSM, Ethernet, Modbus, Canbus, RID protocol	available

#### REMOTE MONITORING FUNCTIONS

<b>mains voltage L1, L2, L3</b>	in V, AC	available	<b>engine temperature</b>	in °C,	optional
<b>generator voltage L1, L2, L3</b>	in V, AC	available	<b>environment temperature</b>	in °C,	optional
<b>genset battery voltage DC</b>	in V, DC	available	<b>generator run hours</b>	in h,	available
<b>mains power total</b>	in kW,	available	<b>generator maintenance hours</b>	in h,	available
<b>generator power total</b>	in kW,	available	<b>fuel level</b>	in L,	available
<b>mains frequency</b>	in Hz	available	<b>load on mains</b>	indication	available
<b>generator frequency</b>	in Hz	available	<b>load on generator</b>	indication	available
<b>current L1, L2, L3</b>	in A,	available	<b>mains supply</b>	indication	available
<b>power L1, L2, L3</b>	in kW,	available	<b>generator supply</b>	indication	available

#### SPECIFIC ALARMS

GENSET DOOR OPEN	FUEL TANK OPEN	AIR FILTER CLOGGING	FIRE ALARM
optional	optional	optional	optional