

Zone amplifier with 6 output zones with independent volume control, BT/USB/SD/MP3 recorder/player with digital FM tuner and possibility to page using microphone with zone selector mod. MZ-62.

Suitable for commercial installations with several loudspeaker zones with the need for piped music and paging in different zones.



MPZ-6241

CHARACTERISTICS	<p>Class D zone amplifier. 6 selectable loudspeaker zones with independent volume control, 50 W maximum per zone. BT/USB/SD/MP3 recorder/player. Digital FM radio tuner. Phantom power supply. Priority paging. Chimes. Connection of up to 6 paging microphones with zone selector M-62. Remote control for player.</p>
POWER	240 W RMS
RESPONSE	80-16,000 Hz \pm 3 dB
DISTORTION	Harmonic: < 0.1%
INPUTS	<p>4 balanced mics/lines, combo (XLR and 6.3 mm jack) 600 Ohm 5 mV RMS and 10,000 Ohm 350 mV RMS, switchable 2 aux, 2 x RCA 47,000 Ohm 150 mV RMS 1 TEL, 10,000 Ohm 700 mV RMS screw terminals 1 EMC, 10,000 Ohm 700 mV RMS screw terminals 2 mics with zone selector, RJ-45</p>
OUTPUTS	1 aux, 2 x RCA 1 V
CONTROLS	<p>Inputs 1 to 6: bass, treble and volume TEL: volume Siren: volume Chime: volume Zones 1 to 6: volume</p>
S/N RATIO	<p>Mic > 65 dB Line > 70 dB</p>
PROTECTION	Temperature and overload
PHANTOM	48 V on mics 1 to 4, selectable
PRIORITY	EMC, siren, TEL and M-62 announcements, chime and Mic 1
IMPEDANCE	4 -16 Ohm 100 and 70 V lines, screw terminals
POWER SUPPLY	<p>230 V AC, 320 W maximum and 24 V DC, 8 A 115 v AC on request</p>
DIMENSIONS	484 x 88 x 353 mm depth. 2 U 19" rack
WEIGHT	8.2 kg
ACCESSORIES	FM antennae

OPTIONAL

M-62: Microphone with zone selector