

PUBLIC ADDRESS / AMPLIFIERS / MONO

MA-91RUZ

PA MULTI-ZONE AMPLIFIER



- ✓ Excellent features
- ✓ Independent volume control for 2 zones
- ✓ Compact size, for desktop use

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Public address amplifier with USB/SD player and FM digital tuner. Suitable for commercial installations, sound coverage and distributed audio.



+ Info:
<https://fonestar.com/MA-91RUZ>

TECHNICAL CHARACTERISTICS

FEATURES	Public address amplifier. 2 speaker zones with independent volume control. USB/SD player. Digital FM radio tuner. Phantom power supply. Input for connection to public address system. Priority paging.
POWER	90 W RMS
RESPONSE	Microphones: 80–18,000 Hz Aux: 50–20,000 Hz
DISTORTION	Harmonic: < 1%
S/N RATIO	Microphones: > 60 dB Aux: > 70 dB
INPUTS	2 balanced mics/lines, combo (XLR and 6.3 mm jack) 1 mV and 50 mV switchable 1 aux, 2 x RCA, 90 mV RMS and 3.5 mm jack, 45 mV RMS 1 100 V line, spring terminals
OUTPUTS	1 line out, 2 x RCA, 700 mV RMS
CONTROLS	Tone: Bass: ±10 dB Treble: ±10 dB Volume: inputs 1 to 2, zones 1 to 2, aux/mp3, master volume and USB/SD/FM player Gain: 100 V line input
PLAYER	USB/SD player and digital FM tuner with presets and auto scan
PHANTOM	24 V in mics 1 to 2, selectable
PRIORITY	Priority 1: 100 V input by signal level Priority 2: Micro 1, 2 by signal level (same priority level)
IMPEDANCE	4 Ohm and 100 and 70 V lines, screw terminals
POWER SUPPLY	230/115 V AC, 125 W
DIMENSIONS	420 x 89 x 320 mm depth. 2 U 19" rack
WEIGHT	6.4 kg
ACCESSORIES	FM antenna 2 x 19" rack mounts



+ Info:
<https://fonestar.com/MA-91RUZ>