

MODBUS REGISTER TABLE							RGT-12SVC
ADDRESS (DEC)	ADDRESS (HEX)	PARAMETER	R/W	RANGE	UNIT	MULTIPLIER	FORMAT
2048	800	THDV L1 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2050	802	THDV L1 #3	R		%	0,1	UNSIGNED 16-BIT
2052	804	THDV L1 #5	R		%	0,1	UNSIGNED 16-BIT
2054	806	THDV L1 #7	R		%	0,1	UNSIGNED 16-BIT
2056	808	THDV L1 #9	R		%	0,1	UNSIGNED 16-BIT
2058	80A	THDV L1 #11	R		%	0,1	UNSIGNED 16-BIT
2060	80C	THDV L1 #13	R		%	0,1	UNSIGNED 16-BIT
2062	80E	THDV L1 #15	R		%	0,1	UNSIGNED 16-BIT
2064	810	THDV L1 #17	R		%	0,1	UNSIGNED 16-BIT
2066	812	THDV L1 #19	R		%	0,1	UNSIGNED 16-BIT
2068	814	THDV L1 #21	R		%	0,1	UNSIGNED 16-BIT
2070	816	THDV L1 #23	R		%	0,1	UNSIGNED 16-BIT
2072	818	THDV L1 #25	R		%	0,1	UNSIGNED 16-BIT
2074	81A	THDV L1 #27	R		%	0,1	UNSIGNED 16-BIT
2076	81C	THDV L1 #29	R		%	0,1	UNSIGNED 16-BIT
2078	81E	THDV L1 #31	R		%	0,1	UNSIGNED 16-BIT
2079	81F	THDV L2 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2081	821	THDV L2 #3	R		%	0,1	UNSIGNED 16-BIT
2083	823	THDV L2 #5	R		%	0,1	UNSIGNED 16-BIT
2085	825	THDV L2 #7	R		%	0,1	UNSIGNED 16-BIT
2087	827	THDV L2 #9	R		%	0,1	UNSIGNED 16-BIT
2089	829	THDV L2 #11	R		%	0,1	UNSIGNED 16-BIT
2091	82B	THDV L2 #13	R		%	0,1	UNSIGNED 16-BIT
2093	82D	THDV L2 #15	R		%	0,1	UNSIGNED 16-BIT
2095	82F	THDV L2 #17	R		%	0,1	UNSIGNED 16-BIT
2097	831	THDV L2 #19	R		%	0,1	UNSIGNED 16-BIT
2099	833	THDV L2 #21	R		%	0,1	UNSIGNED 16-BIT
2101	835	THDV L2 #23	R		%	0,1	UNSIGNED 16-BIT
2103	837	THDV L2 #25	R		%	0,1	UNSIGNED 16-BIT
2105	839	THDV L2 #27	R		%	0,1	UNSIGNED 16-BIT
2107	83B	THDV L2 #29	R		%	0,1	UNSIGNED 16-BIT
2109	83D	THDV L2 #31	R		%	0,1	UNSIGNED 16-BIT
2110	83E	THDV L3 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2112	840	THDV L3 #3	R		%	0,1	UNSIGNED 16-BIT
2114	842	THDV L3 #5	R		%	0,1	UNSIGNED 16-BIT
2116	844	THDV L3 #7	R		%	0,1	UNSIGNED 16-BIT
2118	846	THDV L2 #9	R		%	0,1	UNSIGNED 16-BIT
2120	848	THDV L3 #11	R		%	0,1	UNSIGNED 16-BIT
2122	84A	THDV L3 #13	R		%	0,1	UNSIGNED 16-BIT
2124	84C	THDV L3 #15	R		%	0,1	UNSIGNED 16-BIT
2126	84E	THDV L3 #17	R		%	0,1	UNSIGNED 16-BIT
2128	850	THDV L3 #19	R		%	0,1	UNSIGNED 16-BIT
2130	852	THDV L3 #21	R		%	0,1	UNSIGNED 16-BIT
2132	854	THDV L3 #23	R		%	0,1	UNSIGNED 16-BIT
2134	856	THDV L3 #25	R		%	0,1	UNSIGNED 16-BIT
2136	858	THDV L3 #27	R		%	0,1	UNSIGNED 16-BIT

MODBUS REGISTER TABLE							RGT-12SVC
ADDRESS (DEC)	ADDRESS (HEX)	PARAMETER	R/W	RANGE	UNIT	MULTIPLIER	FORMAT
2138	85A	THDV L3 #29	R		%	0,1	UNSIGNED 16-BIT
2140	85C	THDV L3 #31	R		%	0,1	UNSIGNED 16-BIT
2141	85D	THDI L1 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2143	85F	THDI L1 #3	R		%	0,1	UNSIGNED 16-BIT
2145	861	THDI L1 #5	R		%	0,1	UNSIGNED 16-BIT
2147	863	THDI L1 #7	R		%	0,1	UNSIGNED 16-BIT
2149	865	THDI L1 #9	R		%	0,1	UNSIGNED 16-BIT
2151	867	THDI L1 #11	R		%	0,1	UNSIGNED 16-BIT
2153	869	THDI L1 #13	R		%	0,1	UNSIGNED 16-BIT
2155	86B	THDI L1 #15	R		%	0,1	UNSIGNED 16-BIT
2157	86D	THDI L1 #17	R		%	0,1	UNSIGNED 16-BIT
2159	86F	THDI L1 #19	R		%	0,1	UNSIGNED 16-BIT
2161	871	THDI L1 #21	R		%	0,1	UNSIGNED 16-BIT
2163	873	THDI L1 #23	R		%	0,1	UNSIGNED 16-BIT
2165	875	THDI L1 #25	R		%	0,1	UNSIGNED 16-BIT
2167	877	THDI L1 #27	R		%	0,1	UNSIGNED 16-BIT
2169	879	THDI L1 #29	R		%	0,1	UNSIGNED 16-BIT
2171	87B	THDI L1 #31	R		%	0,1	UNSIGNED 16-BIT
2172	87C	THDI L2 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2174	87E	THDI L2 #3	R		%	0,1	UNSIGNED 16-BIT
2176	880	THDI L2 #5	R		%	0,1	UNSIGNED 16-BIT
2178	882	THDI L2 #7	R		%	0,1	UNSIGNED 16-BIT
2180	884	THDI L2 #9	R		%	0,1	UNSIGNED 16-BIT
2182	886	THDI L2 #11	R		%	0,1	UNSIGNED 16-BIT
2184	888	THDI L2 #13	R		%	0,1	UNSIGNED 16-BIT
2186	88A	THDI L2 #15	R		%	0,1	UNSIGNED 16-BIT
2188	88C	THDI L2 #17	R		%	0,1	UNSIGNED 16-BIT
2190	88E	THDI L2 #19	R		%	0,1	UNSIGNED 16-BIT
2192	890	THDI L2 #21	R		%	0,1	UNSIGNED 16-BIT
2194	892	THDI L2 #23	R		%	0,1	UNSIGNED 16-BIT
2196	894	THDI L2 #25	R		%	0,1	UNSIGNED 16-BIT
2198	896	THDI L2 #27	R		%	0,1	UNSIGNED 16-BIT
2200	898	THDI L2 #29	R		%	0,1	UNSIGNED 16-BIT
2202	89A	THDI L2 #31	R		%	0,1	UNSIGNED 16-BIT
2203	89B	THDI L3 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2205	89D	THDI L3 #3	R		%	0,1	UNSIGNED 16-BIT
2207	89F	THDI L3 #5	R		%	0,1	UNSIGNED 16-BIT
2209	8A1	THDI L3 #7	R		%	0,1	UNSIGNED 16-BIT
2211	8A3	THDI L3 #9	R		%	0,1	UNSIGNED 16-BIT
2213	8A5	THDI L3 #11	R		%	0,1	UNSIGNED 16-BIT
2215	8A7	THDI L3 #13	R		%	0,1	UNSIGNED 16-BIT
2217	8A9	THDI L3 #15	R		%	0,1	UNSIGNED 16-BIT
2219	8AB	THDI L3 #17	R		%	0,1	UNSIGNED 16-BIT
2221	8AD	THDI L3 #19	R		%	0,1	UNSIGNED 16-BIT
2223	8AF	THDI L3 #21	R		%	0,1	UNSIGNED 16-BIT
2225	8B1	THDI L3 #23	R		%	0,1	UNSIGNED 16-BIT

MODBUS REGISTER TABLE							RGT-12SVC
ADDRESS (DEC)	ADDRESS (HEX)	PARAMETER	R/W	RANGE	UNIT	MULTIPLIER	FORMAT
2227	8B3	THDI L3 #25	R		%	0,1	UNSIGNED 16-BIT
2229	8B5	THDI L3 #27	R		%	0,1	UNSIGNED 16-BIT
2231	8B7	THDI L3 #29	R		%	0,1	UNSIGNED 16-BIT
2233	8B9	THDI L3 #31	R		%	0,1	UNSIGNED 16-BIT
2234	8BA	THDV L12 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2236	8BC	THDV L12 #3	R		%	0,1	UNSIGNED 16-BIT
2238	8BE	THDV L12 #5	R		%	0,1	UNSIGNED 16-BIT
2240	8C0	THDV L12 #7	R		%	0,1	UNSIGNED 16-BIT
2242	8C2	THDV L12 #9	R		%	0,1	UNSIGNED 16-BIT
2244	8C4	THDV L12 #11	R		%	0,1	UNSIGNED 16-BIT
2246	8C6	THDV L12 #13	R		%	0,1	UNSIGNED 16-BIT
2248	8C8	THDV L12 #15	R		%	0,1	UNSIGNED 16-BIT
2250	8CA	THDV L12 #17	R		%	0,1	UNSIGNED 16-BIT
2252	8CC	THDV L12 #19	R		%	0,1	UNSIGNED 16-BIT
2254	8CE	THDV L12 #21	R		%	0,1	UNSIGNED 16-BIT
2256	8D0	THDV L12 #23	R		%	0,1	UNSIGNED 16-BIT
2258	8D2	THDV L12 #25	R		%	0,1	UNSIGNED 16-BIT
2260	8D4	THDV L12 #27	R		%	0,1	UNSIGNED 16-BIT
2262	8D6	THDV L12 #29	R		%	0,1	UNSIGNED 16-BIT
2264	8D8	THDV L12 #31	R		%	0,1	UNSIGNED 16-BIT
2265	8D9	THDV L23 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2267	8DB	THDV L23 #3	R		%	0,1	UNSIGNED 16-BIT
2269	8DD	THDV L23 #5	R		%	0,1	UNSIGNED 16-BIT
2271	8DF	THDV L23 #7	R		%	0,1	UNSIGNED 16-BIT
2273	8E1	THDV L23 #9	R		%	0,1	UNSIGNED 16-BIT
2275	8E3	THDV L23 #11	R		%	0,1	UNSIGNED 16-BIT
2277	8E5	THDV L23 #13	R		%	0,1	UNSIGNED 16-BIT
2279	8E7	THDV L23 #15	R		%	0,1	UNSIGNED 16-BIT
2281	8E9	THDV L23 #17	R		%	0,1	UNSIGNED 16-BIT
2283	8EB	THDV L23 #19	R		%	0,1	UNSIGNED 16-BIT
2285	8ED	THDV L23 #21	R		%	0,1	UNSIGNED 16-BIT
2287	8EF	THDV L23 #23	R		%	0,1	UNSIGNED 16-BIT
2289	8F1	THDV L23 #25	R		%	0,1	UNSIGNED 16-BIT
2291	8F3	THDV L23 #27	R		%	0,1	UNSIGNED 16-BIT
2293	8F5	THDV L23 #29	R		%	0,1	UNSIGNED 16-BIT
2295	8F7	THDV L23 #31	R		%	0,1	UNSIGNED 16-BIT
2296	8F8	THDV L31 TOTAL	R		%	0,1	UNSIGNED 16-BIT
2298	8FA	THDV L31 #3	R		%	0,1	UNSIGNED 16-BIT
2300	8FC	THDV L31 #5	R		%	0,1	UNSIGNED 16-BIT
2302	8FE	THDV L31 #7	R		%	0,1	UNSIGNED 16-BIT
2304	900	THDV L31 #9	R		%	0,1	UNSIGNED 16-BIT
2306	902	THDV L31 #11	R		%	0,1	UNSIGNED 16-BIT
2308	904	THDV L31 #13	R		%	0,1	UNSIGNED 16-BIT
2310	906	THDV L31 #15	R		%	0,1	UNSIGNED 16-BIT
2312	908	THDV L31 #17	R		%	0,1	UNSIGNED 16-BIT
2314	90A	THDV L31 #19	R		%	0,1	UNSIGNED 16-BIT

MODBUS REGISTER TABLE							RGT-12SVC
ADDRESS (DEC)	ADDRESS (HEX)	PARAMETER	R/W	RANGE	UNIT	MULTIPLIER	FORMAT
2316	90C	THDV L31 #21	R		%	0,1	UNSIGNED 16-BIT
2318	90E	THDV L31 #23	R		%	0,1	UNSIGNED 16-BIT
2320	910	THDV L31 #25	R		%	0,1	UNSIGNED 16-BIT
2322	912	THDV L31 #27	R		%	0,1	UNSIGNED 16-BIT
2324	914	THDV L31 #29	R		%	0,1	UNSIGNED 16-BIT
2326	916	THDV L31 #31	R		%	0,1	UNSIGNED 16-BIT