

Wall mounted amplifier with USB/MicroSD/MP3 player, FM radio and 2 auxiliary inputs.  
Ideal for small PA installations.



## WA-66R

|                 |   |
|-----------------|---|
| CHARACTERISTICS | Stereo wall amplifier.  |
|                 | Bluetooth receiver.   |
|                 | Different bluetooth ID in each amplifier.                       |
|                 | Configurable bluetooth ID and maximum volume via PC connection. |
|                 | Button to pair new bluetooth devices.                           |
|                 | USB/MicroSD MP3 file player.                                    |
|                 | FM radio.   |
|                 | Display showing selected source and track, FM frequency.        |
|                 | Remote control.   |
|                 | For flush or surface-mounting box of 86 x 86 mm.                |
| POWER           | 2 x 10 W RMS at 8 Ohm   |
| MP3 PLAYER      | USB and MicroSD port  |
| TUNER           | Digital FM with 30 presets, storage and auto scan               |
| INPUTS          | 2 aux, screw terminals  |
| OUTPUTS         | Loudspeakers: 8 Ohm, screw terminals                            |
| PRIORITY        | AUX 1 through signal level                                      |
| POWER SUPPLY    | 100-240 V AC, 23 W  |
| COLOUR          | White (RAL 9003)  |
| DIMENSIONS      | Total: 86 x 86 x 38 mm depth                                    |
|                 | Insert: 62 x 67 x 28 mm depth                                   |
|                 | Flush-mounting box: 80 x 80 x 50 depth                          |
| WEIGHT          | 0.1 kg  |
| ACCESSORIES     | Flush-mounting box  |
|                 | Remote control  |
| OPTIONAL        | 46066: surface-mounting box                                     |