



Tornado1200

The All-In-One Battery Charger

The Tornado 1200 is a 6V & 12V Lead-Acid Battery and Lithium-Ion Battery charger. It is a versatile all-in-one product that features a battery maintainer, trickle charger, and battery desulfator. This low-cost device will give you the best possible maintenance technology for your battery. The Tornado 1200 offers multi-step protection for small and large batteries even in cold temperatures and a rugged enclosure that is water-resistant. These features make this a durable battery charger that will last longer and save you money.

Features

- Battery Maintainer, Trickle Charger, and Battery Desulfator
- Includes 5 Charging Modes
- Compatible With 6V & 12V Lead-Acid and 12V Lithium-Ion Batteries up to 80Ah
- Offers a 5-Step Smart Charging Technology
- Charges Two Times Faster Than Ordinary Battery Chargers
- Works In Cold Temperatures
- Provides a Safe 24/7 Connection
- UV Resistant & IP65 Waterproof Enclosure
- Intuitive LED Indicators

What's in the Box

- The Tornado 1200
- 1 User Manual

Specs

- Input Voltage AC: 100-240VAC, 50-60Hz
- Working Voltage AC: 100-240VAC, 50-60Hz
- Power: 25W
- Charging Current: 1.2A(12V) 1.2A(6V)
- Low-Voltage Detection: 1V(12V), 1V(6V)
- Back Current Drain: < 5mA
- Working Temperature: -4°F to 104°F
- Storage Temperature: -4°F to 130°F
- Charger Type: 5 Step Smart Charger
- Type of Batteries: 6V & 12V
- Battery Chemistries: Wet, Gel, MF, CA, EFB, AGM & LIB
- Battery Capacity: Up to 80Ah (6V&12V)
- Dimensions: 6.8x2.8x1.6 inches
- Weight: 1.0 lb