## Wi-Fi Internet Streaming Amplifier with USB/SD/FM/Blue Tooth EA-30W/EA-60W/EA-120W



### **Description:**

Wi-Fi Internet Streaming Amplifier delivering 30W, 60W up to 120W output with Bluetooth and Wi-Fi streaming capability. Controlled from an Android or iOS smart phone, the Wi-Fi module is compatible with freely available apps to stream music and podcasts directly from a Wi-Fi network. Embedded internet radio offers high quality digital audio from almost any online radio station or podcast available worldwide. Subscription services can store online playlists which can be cast directly from the internet without requiring the smart phone to be connected to the network. Wireless streaming of tracks and playlists stored on the smart phone can be sent from within the app or directly via Bluetooth to the amplifier. In addition, the Wi-Fi Internet Streaming Amplifier has inputs for USB and TF card for playback of stored tracks. The Wi-Fi Internet Streaming Amplifier provides a versatile "hands off" background music solution for continuous playback of music from internet services or a choice of other sources for bars, cafes, restaurants, reception areas and house parties. The Wi-Fi Internet streaming Amplifier support multiple zone or multiple room of different music, while it also support multiple mobile to remote control over Wi-Fi, so remote volume and music control is easy for both commercial or home audio applications.

### Feature:

- Compact mini size Wi-Fi Internet Streaming amplifier
- Tabletop Wi-Fi mixer amplifier with Mp3 player, FM radio & blue tooth
- Wi-Fi streaming amplifier with smart phone control
- Free Wi-Fi Legacy Player app for Android or iOS
- Support Spotify, DLNA, airplay, internet radio and any online radio stations.
- Support multiple zone or multiple room of different music
- Support multiple mobile to remote control over Wi-Fi
- With LAN port and WPS to reset Wi-Fi address
- Rate power output at 30W, 60W to 120W
- Speaker output of 100V or 70V & 4 Ohm-8 Ohm-16 Ohm
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and blue tooth
- LED indicators for power, clip, protect and signal
- Mic1 of balanced XLR input with dipswitch of phantom power on/off & highest VOX priority on/off
- Mic/line 2-3 switchable input unbalanced 6.3mm jack
- Line 1-2 input of RCA input and one RCA line output
- Telephone input with secondary priority and MOH (Music on Hold)
- Volume control for Mic1-3, line1-2, TEL, bass/treble and master
- Complete amplifier protection includes short-circuit, clip, overload and high temp
- 230V AC & 24V DC both power supply system

# Wi-Fi Internet Streaming Amplifier with USB/SD/FM/Blue Tooth EA-30W/EA-60W/EA-120W

Specification:			
Model	EA-30W	EA-60W	EA-120W
Description	Wi-Fi Internet Streaming Amplifier with USB/SD/FM/Blue Tooth		
Rated Power Output	30W	60W	120W
Speaker Outputs	100V or 70V & 4 Ohm-8 Ohm-16 Ohm		
Connector	Mic1 input by balanced XLR with phantom power & VOX highest priority		
	Mic/line switchable input 2-3 unbalanced 6.3mm jack		
	Telephone input with secondary priority and MOH (Music on Hold)		
	Line1-2 inputs by RCA; Line output by RCA		
Input	MIC1-3: 5-8mV, 600Ω; Line, 150-470mV, 10KΩ, unbalanced RCA		
Line Out	0.775(0dBV)		
Frequency Response	60Hz-15kHz(±3dB)		
S/N Ratio	Line $\geq$ 85dB, Mic $\geq$ 72dB		
THD	Less than 0.5%		
Protection	Short-circuit, clip, overload and high temp protection		
Power Consumption	60W	100W	200W
Power Supply	230V AC & 24V DC; 50-60Hz		
Dimension	320×210×90mm		
Weight	3.6kg	4.1kg	4.7kg

### **Rear Panel:**

