

V-TAC

Meaningful Innovation.

Portable Power Station 300W



- ⊙ Upgrade to LiFePO4 battery capacity 288Wh, 10 outlets
- ⊙ 1 x DC head 7909 input charging port: adapter charging (24V/2.5A), car charging (12V), solar charging (12-24V 120W MAX)
- ⊙ 2 x DC head 5521 output port and 1 x automobile auxiliary power outlet(total 12V/8A)
- ⊙ Speed charger QC 3.0 Output x 2, TYPE-C : Output PD18W X1, TYPE-C : Output PD65W
- ⊙ 1 x EU / BS standard AC ports
- ⊙ LED Flashlight with SOS
- ⊙ Quiet noise level during operation
- ⊙ Over-current, Over-voltage , over-temperature and Short Circuit Protections 9, Cycle life: 2000 Cycles

V-TAC.EU

|

VTACEXPORTS.COM



LISTING DETAILS

Model: **VT-303N**
 SKU Code: **EU-Plug -11625 | BS-Plug -11740**
 EAN Code: **EU-Plug- 3800170200074**
BS-Plug -3800170203266

MASTER BOX PACKAGING

Qty: **1pc/box**
 Net Weight : **4.3 kgs**
 Product Size : **W*H*L 249*171.5*208mm**

GENERAL DATA

BATTERY	Battery capacity	LiFePO4(IRF32135 19.2V 15Ah/288Wh)	
	Cell model	IRF32135	
DC/INPUT	DC 7909 INPUT	12-20V 120W max Charger	Parallel input
	XT60 Solar Charger	12-24V 120W max Charger	
USB/OUTPUT	USB1 Output	18W 5V3.5A	
	USB2 Output	QC 3.0 18W 5V3A/9V2A/12V1.5A	
	TYPE-C 1 Output	PD18W ,5V3A/9V2A/12V1.5A	
	TYPE-C2 Output	PD65W ,5V3A / 9V3A / 12V3A / 15V3A / 20V3.25A	
DC OUTPUT	DC 1 Output	12V/8A	100W shared
	DC 2 Output	12V/8A	
	Auxiliary Power Outlet	12V/8A	
AC OUTPUT	AC Output 1	AC Power Output 230V Sine WAVE 300W PEAK 500W	
	Output Frequency max	Sine WAVE 300W PEAK 500W	
	Frequency	50Hz	
WIRELESS CHARGER	DC	15W 5V 3A	
LED LIGHTING	Power	3W	
	Mode	High-Light/Low-light/SOS/Flash	

15W Wireless charger

