

OPTONICA



PORTABLE POWER STATION 400W SKU: 9418



Camera (16W)
Around 20 Recharges



Projector (100W)
Around 3.2 Hours



Camping light (125W)
Around 2.6 Hours



Macbook 12
Around 5 Recharges



Car Fridge (60W)
Around 5.4 Hours



Drone (40W)
Around 8 Recharges



Phone (4000mAh)
Around 27 Recharges



Rice cooker (330W)
Around 1.0 Hours



Electric fan (45W)
Around 7.2 Hours



Refrigerator (120W)
Around 2.7 Hours



Photography lights (300W)
Around 1.1 Hours

SPECIFICATIONS

| Output | | |
|--|----------------------------------|----------------------------------|
| AC output | Rated voltage | 230V |
| | Rated power | 400W |
| | Peak power | 800W |
| | Frequency | 50Hz |
| DC*2 Output | Rated voltage | 13.3V |
| | Rated current | 10A |
| DC Output Ciger Socket | Rated voltage | 13.3V |
| | Rated current | 10A |
| USB-A*3 Output | Rated voltage | 5V |
| | Rated current | 2.4A |
| USB-C*1 Output | PD: 60W Max | 5V3A, 9V3A, 12V3A, 15V3A, 20V3A |
| Floodlight | mlm | 200 Low / 800 Middle / 1400 high |
| Input | | |
| DC Input | Rated voltage | 12V-24V(12V 10A) |
| | Rated power | Max 120W |
| USB-C*1 Input | PD: 60W Max | 5V3A, 9V3A, 12V3A, 15V3A, 20V3A |
| DC input and USB-C*1 input at the same time to recharge the power station, the input power can be up to 180W max | | |
| Battery | | |
| Rated capacity | 320Wh | |
| Battery cell type | Lithium-ion | |
| General | | |
| Working environment condition | Relative humidity: 20%-90% | |
| | Temperature: 32-104°F (-10-40°C) | |
| Size | 237.2*195.2*190.6mm±5mm | |



CHARGE FIRST! Before using your new power station, plug it into a suitable power outlet until it is fully charged. Then you can start your exciting journey with it.